Floating-Point Exceptions

7

This chapter describes FPU floating-point exceptions, including FPU exception types, exception trap processing, exception flags, saving and restoring state when handling an exception, and trap handlers for IEEE Standard 754 exceptions.

A floating-point exception occurs whenever the FPU cannot handle either the operands or the results of a floating-point operation in its normal way. The FPU responds by generating an exception to initiate a software trap or by setting a status flag.

7.1 Exception Types

The FP *Control/Status* register described in Chapter 6 contains an *Enable* bit for each exception type; exception *Enable* bits determine whether an exception will cause the FPU to initiate a trap or set a status flag.

- If a trap is taken, the FPU remains in the state found at the beginning of the operation and a software exception handling routine executes.
- If no trap is taken, an appropriate value is written into the FPU destination register and execution continues.

The FPU supports the five IEEE Standard 754 exceptions:

- Inexact (I)
- Underflow (U)
- Overflow (O)
- Division by Zero (Z)
- Invalid Operation (V)

Cause bits, *Enables*, and *Flag* bits (status flags) are used.

The FPU adds a sixth exception type, Unimplemented Operation (E), to use when the FPU cannot implement the standard MIPS floating-point architecture, including cases in which the FPU cannot determine the correct exception behavior. This exception indicates the use of a software implementation. The Unimplemented Operation exception has no *Enable* or *Flag* bit; whenever this exception occurs, an unimplemented exception trap is taken (if the FPU interrupt input to the CPU is enabled).

Figure 7-1 illustrates the *Control/Status* register bits that support exceptions.



Figure 7-1 Control/Status Register Exception/Flag/Trap/Enable Bits

Each of the five IEEE Standard 754 exceptions (V, Z, O, U, I) is associated with a trap under user control, and is enabled by setting one of the five *Enable* bits. When an exception occurs, the corresponding *Cause* bit is set. If the corresponding *Enable* bit is not set, the *Flag* bit is also set. If the corresponding *Enable* bit is set, the *Flag* bit is not set and the FPU generates an interrupt to the CPU. Subsequent exception processing allows a trap to be taken.

7.2 Exception Trap Processing

When a floating-point exception trap is taken, the *Cause* register indicates the floating-point coprocessor is the cause of the exception trap. The Floating-Point Exception (FPE) code is used, and the *Cause* bits of the floating-point *Control/Status* register indicate the reason for the floating-point exception. These bits are, in effect, an extension of the system coprocessor *Cause* register.

7.3 Flags

A *Flag* bit is provided for each IEEE exception. This *Flag* bit is set to a 1 on the assertion of its corresponding exception, with no corresponding exception trap signaled.

The *Flag* bit is reset by writing a new value into the *Status* register; flags can be saved and restored by software either individually or as a group.

When no exception trap is signaled, floating-point coprocessor takes a default action, providing a substitute value for the exception-causing result of the floating-point operation. The particular default action taken depends upon the type of exception. Table 7-1 lists the default action taken by the FPU for each of the IEEE exceptions.

Table 7-1 Default FPU Exception Actions

Field	Description	Rounding Mode	Default action
I	Inexact exception	Any	Supply a rounded result
U	Underflow exception	RN	Modify underflow values to 0 with the sign of the intermediate result
		RZ	Modify underflow values to 0 with the sign of the intermediate result
		RP	Modify positive underflows to the format's smallest positive finite number; modify negative underflows to -0
		RM	Modify negative underflows to the format's smallest negative finite number; modify positive underflows to 0
O	Overflow exception	RN	Modify overflow values to ∞ with the sign of the intermediate result
		RZ	Modify overflow values to the format's largest finite number with the sign of the intermediate result
		RP	Modify negative overflows to the format's most negative finite number; modify positive overflows to + ∞
		RM	Modify positive overflows to the format's largest finite number; modify negative overflows to – ∞
Z	Division by zero	Any	Supply a properly signed ∞
V	Invalid operation	Any	Supply a quiet Not a Number (NaN)

The FPU detects the eight exception causes internally. When the FPU encounters one of these unusual situations, it causes either an IEEE exception or an Unimplemented Operation exception (E).

Table 7-2 lists the exception-causing situations and contrasts the behavior of the FPU with the requirements of the IEEE Standard 754.

Table 7-2 FPU Exception-Causing Conditions

FPA Internal Result	IEEE Standard 754	Trap Enable	Trap Disable	Notes
Inexact result	I	I	I	Loss of accuracy
Exponent overflow	O,I†	O,I	O,I	Normalized exponent > E_{max}
Division by zero	Z	Z	Z	Zero is (exponent = E_{min}-1, mantissa = 0)
Overflow on convert	V	E	E	Source out of integer range
Signaling NaN source	V	V	V	
Invalid operation	V	V	V	0/0, etc.
Exponent underflow	U	E	UI‡	Normalized exponent < E_{min}
Denormalized or QNaN	None	E	E	Denormalized is (exponent = E_{min}-1 and mantissa <> 0)

† The IEEE Standard 754 specifies an inexact exception on overflow only if the overflow trap is disabled.

‡ Exponent underflow sets the U and I *Cause* bits if both the U and I *Enable* bits are not set and the *FS* bit is set; otherwise exponent underflow sets the E *Cause* bit.

7.4 FPU Exceptions

The following sections describe the conditions that cause the FPU to generate each of its exceptions, and details the FPU response to each exception-causing condition.

Inexact Exception (I)

The FPU generates the Inexact exception if one of the following occurs:

- the rounded result of an operation is not exact, or
- the rounded result of an operation overflows, or
- the rounded result of an operation underflows and both the Underflow and Inexact *Enable* bits are not set and the *FS* bit is set.

The FPU usually examines the operands of floating-point operations before execution actually begins, to determine (based on the exponent values of the operands) if the operation can *possibly* cause an exception. If there is a possibility of an instruction causing an exception trap, the FPU uses a coprocessor stall to execute the instruction.

It is impossible, however, for the FPU to predetermine if an instruction will produce an inexact result. If Inexact exception traps are enabled, the FPU uses the coprocessor stall mechanism to execute all floating-point operations that require more than one cycle. Since this mode of execution can impact performance, Inexact exception traps should be enabled only when necessary.

Trap Enabled Results: If Inexact exception traps are enabled, the result register is not modified and the source registers are preserved.

Trap Disabled Results: The rounded or overflowed result is delivered to the destination register if no other software trap occurs.

Invalid Operation Exception (V)

The Invalid Operation exception is signaled if one or both of the operands are invalid for an implemented operation. When the exception occurs without a trap, the MIPS ISA defines the result as a quiet Not a Number (NaN). The invalid operations are:

- Addition or subtraction: magnitude subtraction of infinities, such as: $(+ \infty) + (- \infty)$ or $(- \infty) - (- \infty)$
- Multiplication: 0 times ∞, with any signs
- Division: 0/0, or ∞/∞, with any signs
- Comparison of predicates involving **<** or **>** without **?**, when the operands are unordered
- Comparison or a Convert From Floating-point Operation on a signaling NaN.
- Any arithmetic operation on a signaling NaN. A move (MOV) operation is not considered to be an arithmetic operation, but absolute value (ABS) and negate (NEG) are considered to be arithmetic operations and cause this exception if one or both operands is a signaling NaN.
- Square root: √x, where x is less than zero

Software can simulate the Invalid Operation exception for other operations that are invalid for the given source operands. Examples of these operations include IEEE Standard 754-specified functions implemented in software, such as Remainder: *x* REM *y*, where *y* is 0 or *x* is infinite; conversion of a floating-point number to a decimal format whose value causes an overflow, is infinity, or is NaN; and transcendental functions, such as ln (–5) or cos–1(3). Refer to Appendix B for examples or for routines to handle these cases.

Trap Enabled Results: The original operand values are undisturbed.

Trap Disabled Results: A quiet NaN is delivered to the destination register if no other software trap occurs.

Division-by-Zero Exception (Z)

The Division-by-Zero exception is signaled on an implemented divide operation if the divisor is zero and the dividend is a finite nonzero number. Software can simulate this exception for other operations that produce a signed infinity, such as ln(0), sec($\pi/2$), csc(0), or $0^{-1.}$

Trap Enabled Results: The result register is not modified, and the source registers are preserved.

Trap Disabled Results: The result, when no trap occurs, is a correctly signed infinity.

Overflow Exception (O)

The Overflow exception is signaled when the magnitude of the rounded floating-point result, with an unbounded exponent range, is larger than the largest finite number of the destination format. (This exception also sets the Inexact exception and *Flag* bits.)

Trap Enabled Results: The result register is not modified, and the source registers are preserved.

Trap Disabled Results: The result, when no trap occurs, is determined by the rounding mode and the sign of the intermediate result (as listed in Table 7-1).

Underflow Exception (U)

Two related events contribute to the Underflow exception:

- creation of a tiny nonzero result between $\pm 2^{Emin}$ which can cause some later exception because it is so tiny
- extraordinary loss of accuracy during the approximation of such tiny numbers by denormalized numbers.

IEEE Standard 754 allows a variety of ways to detect these events, but requires they be detected the same way for all operations.

Tininess can be detected by one of the following methods:

- after rounding (when a nonzero result, computed as though the exponent range were unbounded, would lie strictly between $\pm 2^{Emin}$)
- before rounding (when a nonzero result, computed as though the exponent range and the precision were unbounded, would lie strictly between $\pm 2^{Emin}$).

The MIPS architecture requires that tininess be detected after rounding.

Loss of accuracy can be detected by one of the following methods:

- denormalization loss (when the delivered result differs from what would have been computed if the exponent range were unbounded)
- inexact result (when the delivered result differs from what would have been computed if the exponent range and precision were both unbounded).

The MIPS architecture requires that loss of accuracy be detected as an inexact result.

Trap Enabled Results: If Underflow or Inexact traps are enabled, or if the *FS* bit is not set, then an Unimplemented exception (E) is generated, and the result register is not modified.

Trap Disabled Results: If Underflow and Inexact traps are not enabled and the *FS* bit is set, the result is determined by the rounding mode and the sign of the intermediate result (as listed in Table 7-1).

Unimplemented Instruction Exception (E)

Any attempt to execute an instruction with an operation code or format code that has been reserved for future definition sets the *Unimplemented* bit in the *Cause* field in the FPU *Control/Status* register and traps. The operand and destination registers remain undisturbed and the instruction is emulated in software. Any of the IEEE Standard 754 exceptions can arise from the emulated operation, and these exceptions in turn are simulated.

The Unimplemented Instruction exception can also be signaled when unusual operands or result conditions are detected that the implemented hardware cannot handle properly. These include:

- Denormalized operand, except for Compare instruction
- Quiet Not a Number operand, except for Compare instruction
- Denormalized result or Underflow, when either Underflow or Inexact *Enable* bits are set or the *FS* bit is not set.
- Reserved opcodes
- Unimplemented formats
- Operations which are invalid for their format (for instance, CVT.S.S)

NOTE: Denormalized and NaN operands are only trapped if the instruction is a convert or computational operation. Moves do not trap if their operands are either denormalized or NaNs.

The use of this exception for such conditions is optional; most of these conditions are newly developed and are not expected to be widely used in early implementations. Loopholes are provided in the architecture so that these conditions can be implemented with assistance provided by software, maintaining full compatibility with the IEEE Standard 754.

Trap Enabled Results: The original operand values are undisturbed.

Trap Disabled Results: This trap cannot be disabled.

7.5 Saving and Restoring State

Sixteen doubleword coprocessor load or store operations save or restore the coprocessor floating-point register state in memory. The remainder of control and status information can be saved or restored through Move To/From Coprocessor Control Register instructions, and saving and restoring the processor registers. Normally, the *Control/Status* register is saved first and restored last.

When the coprocessor *Control/Status* register (*FCR31*) is read, and the coprocessor is executing one or more floating-point instructions, the instruction(s) in progress are either completed or reported as exceptions. The architecture requires that no more than one of these pending instructions can cause an exception. If the pending instruction cannot be completed, this instruction is placed in the *Exception* register, if present. Information indicating the type of exception is placed in the *Control/Status* register. When state is restored, state information in the status word indicates that exceptions are pending.

Writing a zero value to the *Cause* field of *Control/Status* register clears all pending exceptions, permitting normal processing to restart after the floating-point register state is restored.

The *Cause* field of the *Control/Status* register holds the results of only one instruction; the FPU examines source operands before an operation is initiated to determine if this instruction can possibly cause an exception. If an exception is possible, the FPU executes the instruction in stall mode to ensure that no more than one instruction (that might cause an exception) is executed at a time.

7.6 Trap Handlers for IEEE Standard 754 Exceptions

The IEEE Standard 754 strongly recommends that users be allowed to specify a trap handler for any of the five standard exceptions that can compute; the trap handler can either compute or specify a substitute result to be placed in the destination register of the operation.

By retrieving an instruction using the processor *Exception Program Counter (EPC*) register, the trap handler determines:

- exceptions occurring during the operation
- the operation being performed
- the destination format

On Overflow or Underflow exceptions (except for conversions), and on Inexact exceptions, the trap handler gains access to the correctly rounded result by examining source registers and simulating the operation in software.

On Overflow or Underflow exceptions encountered on floating-point conversions, and on Invalid Operation and Divide-by-Zero exceptions, the trap handler gains access to the operand values by examining the source registers of the instruction.

The IEEE Standard 754 recommends that, if enabled, the overflow and underflow traps take precedence over a separate inexact trap. This prioritization is accomplished in software; hardware sets the bits for both the Inexact exception and the Overflow or Underflow exception.